

The DHA VT2-Twin-Bass "Custom Shop"

Thank you for purchasing the DHA VT2-Twin-Bass overdrive and distortion effects pedal, we are sure you will be very happy with it. The VT2-Twin-Bass uses two 12AX7 (ECC83) valves to generate classic pure valve tones. There are two separate selectable channels Red or Blue. The VT2-Twin-Bass is capable of producing a very wide range of gains to suit all types of playing. It is intended to be used in front of a valve amplifier, but will also work well with solid state amps or even recording set ups acting as a valve pre-amp.



The VT2-Twin-Bass has two built-in voltage doubler circuits; this generates 24V from the existing 12V power supply. The 24V is used to supply the anodes or plates of the valves, two are used to ensure good power supply decoupling between channels.

The VT2-Twin-Bass is fitted with 2.1mm external PSU adaptor for use with a 12v @1200mA external supply. The user should use a well regulated external supply as the better the regulation then the less the hum when at higher gain levels. If you find there is a lot of hum at high gains then the problem will be the supply is not well regulated. I have found that Switchmode supplies work well and these are standard for higher current

types, so it is likely that any 12V supply over 1.25A will be a switchmode. The inner of the connector is the positive, there is reverse polarity protection so no harm will be done if you get it wrong.

Blue channel - This channel is clean to crunch using both stages of the first valve. There is a common I/P pad control between the Red and Blue channels and blue Gain and Level controls. When the Blue channel is selected via the Red or Blue foot switch then the right hand side valve will light Blue.

Red channel - This channel is clean to overdrive using a shared first stage of one valve and both stages of the second valve giving 3 valve stages in all. The Red channel controls are I/P pad, Gain, Overdrive, Level. When the Red channel is select via the Red or Blue foot switch then the right hand side valve will light Red.

Red or Blue Level sets the output level of the effect to your amplifier, there is a lot of gain generated by the valves and this will overdrive the input of your guitar amplifier with ease.

Red or Blue Gain sets the level into the second stage of the valve on the selected channel and hence the level of gain. Use your volume control on your guitar to control the gain on the first stage of the valve, you will find that the VT2-Twin-Bass responses very well to this and you can control the break-up distortion like this.

Red Overdrive sets the level into the second stage of the valve on the Red channel and hence the level of Overdrive on that channel.

The I/P pad is useful when using high output or active pickups or when using the effect in a line level loop. The I/P Pad control is common to both channels.

So, just plug your bass into the jack with the bass drawing and your amplifier into the jack with the amp drawing and you are off and running!

Your pedal is covered for any parts and labour required to repair it should it go wrong within 12mths of purchase. This does not cover misuse of the product but we will be happy to repair this at cost as we will for any units

which fail outside of the 12mths. The owner of a faulty pedal will pay all the postage costs. Here at DHA we take a great pride in all our effects and amplifiers and we welcome comments from our customers at davehallamps@aol.com

Once again we thank you for your purchase and we wish you luck and lots of fun with your music.

Best regards
Dave Hall Amps